# CKSH-SQUICH® 3 and 4 poles + 10A - 400V SQUICH®



enclosures: size "21.21" page:

Insulating type 339 - 348

Metallic type 349 - 363

W-TYPE for aggressive environments 512 - 518

E-Xtreme® corrosion proof 538 - 539

EMC 564 - 572

IP68 628 - 631

- can be mated with CK inserts

inserts, 3 poles + spring terminal connection without tools



inserts, 4 poles + spring terminal connection without tools



description	part No.	part No.
female inserts with female contacts male inserts with male contacts	CKSHF 03 CKSHM 03	

- characteristics according to EN 61984:

female inserts with female contacts

male inserts with male contacts


10A 400V 4kV 3 10A 690V 4kV 2

- c Nus (UL for USA and Canada), DNV-GL


- rated voltage according to UL/CSA: 600V


- insulation resistance: ≥ 10 GΩ
- ambient temperature limits: -40 °C ... +125 °C
- made of self-extinguishing thermoplastic resin UL 94V-0
- mechanical life: ≥ 500 cycles
- contact resistance: ≤ 3 mΩ
- for max. current load see the connector inserts derating diagrams below; for more information see page 28

#### CKSH 03 poles connector inserts Maximum current load derating diagram



## CKSH 04 poles connector inserts Maximum current load derating diagram





contacts side (front view)






 inserts for wires with the following cross-sectional areas: 0,14 - 2,5 mm² - AWG 26 - 14 for prepared wires useable section: up to 1.5 mm² (AWG 16)

- conductor stripping length: 9...11 mm



## SQUICH®-spring connection technology WIRING




Deeply insert a stripped conductor into a round terminal.

Push the actuator button to close the terminal.

### **RE-OPENING**



Insert a **0,5 x 3,5 mm** flat blade screwdriver in the actuator button side window and pull it up by levering down.



contacts side (front view)



CKSHF 04



- inserts for wires with the following cross-sectional areas: 0,14 2,5 mm² AWG 26 14 for prepared wires useable section: up to 1,5 mm² (AWG 16)
- conductor stripping length: 9...11 mm



Rear top entry of wires for a more easier wiring

